

Seqrite Endpoint Security 7.6 Administrator's Guide

วิธีการตั้งค่าให้เครื่อง Client ไม่สามารถเชื่อมต่อ Wifi ตัวอื่นได้

SEPS SME SEPS Business SEPS Total SEPS Enterprise Suit

<u>วิธีการตั้งค่าให้เครื่อง Client ไม่สามารถเชื่อมต่อ Wifi ตัวอื่นได้</u>

1. เข้าสู่หน้า Console Seqrite Endpoint Security Management

ไปที่เมนู Clients > แถบ Manage Policies > เลือก Policy ที่ต้องการตั้งค่า

Corrito	Welcome Administrator		nistrator 🄅 Admin	🔅 Admin Settings 📞 Support ? Help 🗗 Logout			
Endpoint Security	7.6 Total		Home	Clients Settings	Reports 💄 🞽		
Clients							
Client Status Clie	ent Action Client	Deployment Manag	ge Groups Manage F	Policies Assets			
Policies help you manage the the policy applied on the end	client settings for differen points.	t groups within your organiza	tion. Here you can create and	Delete	iew policy details and status of		
Policy Name	Groups	Access	Policy Applied On	Policy Pending On	Action		
Default	-	Default	-	-	6		
Import_Policy (i)	Default	Default	-	1 Endpoint	e		
Client_Policy	Client	Default	1 Endpoint	-	e		

2. ไปที่ Advanced Device Control > ติ๊กช่องสี่เหลี่ยม Enable Advanced Device Control

> ติ๊กช่องหมวด Wireless > ตรง Wifi ดรอปดาวน์ ให้เลือก Allow > จากนั้นกด Customize

Scan Settings Email Settings	Advanced Device Control	1			
External Drives Settings	Device Types Exceptions	5			
IDS/IPS	Select Access Policy for Device Type	es			
Firewall	Storage Devices		Card Readers		
Web Security	USB Storage Device 🕐	Allow -	Card Reader Device (MTD) <table-cell></table-cell>	Allow	
Application Control	CD/DVD	Allow	Card Reader Device (SCSI) <table-cell></table-cell>	Allow	
Data Loss Prevention	Internal Card Reader 🕜	Allow -			
File Activity Monitor	Internal Floppy Drive	Allow	Mobile & Portable Devices		
Update Settings	ZIP Drive	Allow	Windows Portable Device <table-cell></table-cell>	Allow 👻	
Internet Settings			iPhone	Allow -	
Patch Server	Vireless		iPad	Allow -	
General Settings	Wi-Fi ? Customize	Allow 🗸	iPod	Allow	
	Bluetooth ?	Block Allow	BlackBerry	Allow	
		Block if wired connection is available	Mobile Phones (Symbian) 👔	Allow -	
	Interface		Scanner & Imaging Devices	Allow	

 ติ๊กเลือก Allow only for authorized Wi-Fi access points > ใส่ SSID กับ Mac Address ที่เรา ต้องการให้เชื่อมต่อได้ > Add > กด OK

External Drives Settings						
IDS/IPS	Select Access Policy for	Device Types			-	
Firewall	Authorized Wi-Fi conn	lections		>	٢	
Web Security	 Allow for all Wi-Fi acc Allow only for author 	cess points rized Wi-Fi access poin	ts		Allow	
Application Control	Enter Network Data:				Allow	
Advanced Device Control	SSID :	Nextech5G		7	Allow	
Data Loss Prevention						
File Activity Monitor	MAC Address :	94:E9:79:74:2F:25		Add		
Update Settings	SSID		MAC Address	Delete	Allow	
Internet Settings	Nextech		94:E9:79:74:2F:24		Allow	
Patch Server					Allow	
General Settings					Allow	
_	OK Can	ncel			Allow	

4. ทำการ Save Policy เป็นอันเสร็จสิ้น

Others
Local Printers Allow -
Teensy Board ? Policy settings saved successfully.
Network Share OK
Unknown Device
Default Note: Please refer the Administrator Guide for details about settings which are applicable as per the platform.
Save Policy Cancel